

LED PAR LIGHT



MODEL: WKP-5401/WKP-5403

WKP-F5401/WKP-F5403



WECAN SCIENCE TECHNOLOGY LIGHTING CO.,LTD

[HTTP://WWW.WECANLIGHT.COM](http://www.wecanlight.com)

MODEL: WKP-5401/WKP-5403/WKP-F5401/WKP-F5403

Channel: 8 DMX

Lamp: 54*1W/54*3W LED RGBW(R=12,G=18,B=18,W=6)

Control: DMX, Master Slave Mode, Auto Mode

Power: AC 90-240V/50-60HZ

Power consumption: 80W/200W

Size: 24.5*24.5*34CM

N.W: 4KG/8.5KG

G.W: 4.8KG/9KG

Display: digit

WaterProof: WKP-5401/WKP-5403 IP56;WKP-F5401/WKP-F5403 IP65

一: Display panel operation

Push "MANU" into main menu, push "UP" "DOWN" Choose submenu, push "ENTER"

- d001 ⇨ d512 ⇨ 4CH mode
- A001 ⇨ A512 ⇨ 8CH mode
- FF01 ⇨ FF99 ⇨ RGB Color gradient
- CC01 ⇨ CC99 ⇨ RGBW Color jumping
- EE01 ⇨ EE99 ⇨ Auto color
- dEoo ⇨ dEoo ⇨ AUTO
- SoUd ⇨ SoUd ⇨ SOUND

二: Master mode

2 sets or above light Be connected by signal line, set any host computer for demo programs or gradient, jumping, the other light is set to receive address d001 or A001.



三: Channel

4 Channel		
Channel	numerical	Functional description
CH1	0	Red close
	1-255	Red dimmer
CH2	0	Green close
	1-255	Green dimmer
CH3	0	Bule close
	1-255	Bule dimmer
CH4	0	White close
	1-255	White dimmer
8 Channel		
Channel	numerical	Functional description
CH1	0-255	DIMMER
CH2	0	Red close
	1-255	Red dimmer
CH3	0	Green close
	1-255	Green dimmer
CH4	0	Bule close
	1-255	Bule dimmer
CH5	0	White close
	1-255	White dimmer
CH6	0-255	Strobe
CH7	0-255	Speed
CH8	0-50	Open CH1-CH5
	51-100	auto color
	101-150	Color gradient
	151-200	Color jumping
	201-250	Auto
	251-255	Sound